

EPM-50 Power Meter

FIBERBASIX 50 TESTER



SPEC SHEET

Allows power measurements up to 26 dBm with battery autonomy of over 300 hours; comes with a specific high power configuration for CATV and Telco markets.

KEY FEATURES

Rugged design

Interchangeable connector adapters

300 hours of battery life

Tone recognition for fiber identification

Universal push-pull interface

Reference function for direct loss measurements

APPLICATIONS

High power model for CATV and Telco applications

Enterprise/LAN for singlemode and multimode measurements

COMPLEMENTARY PRODUCTS



Optical Light Source
ELS-50



Fiber Inspector Probe
FIP-400



Visual Fault Locator
FLS-240



- 1 Rubber boot protector
- 2 Wrist strap
- 3 Cap protector
- 4 Stand

SPECIFICATIONS^a

MODEL	EPM-53	EPM-53X
Power meter port	InGaAs	InGaAsX
Power range ^b (dBm)	10 to -60	26 to -50
Number of calibrated wavelengths ^c	5	5
Power uncertainty ^d	±5 %	±5 %
Resolution (dB)	0.01	0.01
Display units	dB/dBm/W	dB/dBm/W
Tone detection (Hz)	270, 1 k, 2 k	270, 1 k, 2 k
Battery life (hours) ^d	>300	>300
Warranty (year)	1	1

GENERAL SPECIFICATIONS

Size (H x W x D)	189 mm x 78 mm x 37 mm (7 7/16 in x 3 1/16 in x 1 7/16 in)
Weight	0.4 kg (0.9 lb)
Temperature	operating -10 °C to 50 °C (14 °F to 122 °F) storage -40 °C to 70 °C (-40 °F to 158 °F)
Relative humidity	0 % to 95 % non-condensing

STANDARD ACCESSORIES

Soft pouch, PMA-22 FC connector adapter, quick reference sticker in five languages, Certificate of Calibration, Certificate of Compliance, three AA batteries

OPTIONAL ACCESSORIES

PMA-22 (FC connector adapter for EPM-50 power meter)	Manual (user guide)
PMA-32 (ST connector adapter for EPM-50 power meter)	GP-10-081 (soft pouch)
PMA-54 (SC connector adapter for EPM-50 power meter)	GP-2124 (rubber boot)

Notes

- a. All specifications valid at 23 °C ± 3 °C, with an FC/UPC connector.
- b. In CW mode.
- c. Wavelengths: 850 nm, 1300 nm, 1310 nm, 1490 nm, 1550 nm.
- d. Typical.

ORDERING INFORMATION

EPM-5X-PMA-22-XX

EPM-53 = InGaAs detector ■
 EPM-53X = High-power InGaAs detector ■
 Example: EPM-53X-PMA-22-RB

RB = With rubber boot protector
 00 = Without rubber boot protector
 PMA-22 = FC adapter for power meter

EXFO Corporate Headquarters > 400 Godin Avenue, Quebec City (Quebec) G1M 2K2 CANADA | Tel.: +1 418 683-0211 | Fax: +1 418 683-2170 | info@EXFO.com

			Toll-free: +1 800 663-3936 (USA and Canada) www.EXFO.com	
EXFO America	3701 Plano Parkway, Suite 160	Plano, TX 75075 USA	Tel.: +1 800 663-3936	Fax: +1 972 836-0164
EXFO Asia	151 Chin Swee Road, #03-29 Manhattan House	SINGAPORE 169876	Tel.: +65 6333 8241	Fax: +65 6333 8242
EXFO China	36 North, 3 rd Ring Road East, Dongcheng District Room 1207, Tower C, Global Trade Center	Beijing 100013 P. R. CHINA	Tel.: +86 10 5825 7755	Fax: +86 10 5825 7722
EXFO Europe	Omega Enterprise Park, Electron Way	Chandlers Ford, Hampshire S053 4SE ENGLAND	Tel.: +44 2380 246810	Fax: +44 2380 246801
EXFO NetHawk	Elektronikkatie 2	FI-90590 Oulu, FINLAND	Tel.: +358 (0)403 010 300	Fax: +358 (0)8 564 5203
EXFO Service Assurance	270 Billerica Road	Chelmsford, MA 01824 USA	Tel.: +1 978 367-5600	Fax: +1 978 367-5700

EXFO is certified ISO 9001 and attests to the quality of these products. This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. EXFO has made every effort to ensure that the information contained in this specification sheet is accurate. However, we accept no responsibility for any errors or omissions, and we reserve the right to modify design, characteristics and products at any time without obligation. Units of measurement in this document conform to SI standards and practices. In addition, all of EXFO's manufactured products are compliant with the European Union's WEEE directive. For more information, please visit www.EXFO.com/recycle. Contact EXFO for prices and availability or to obtain the phone number of your local EXFO distributor.

For the most recent version of this spec sheet, please go to the EXFO website at www.EXFO.com/specs.

In case of discrepancy, the Web version takes precedence over any printed literature.